

MINISC2 V1 (10CH DMX)

DMX TABELLA FOR MINISCAN2-V1 (10CH DMX)					
CHANNEL	FUNKCION	TYPE OF CONTROL	EFFECT	PERCENT	DECIMAL
1	X mirror	proportional	proportional control of the X movement	0 / 100%	0 - 255
2	Y mirror	proportional	proportional control of the y movement	0 / 100%	0 - 255
3	GOBO	step	gobo1		0 - 18
		step	gobo2		28 - 37
		step	gobo3		47 - 56
		step	gobo4		66 - 75
		step	gobo5		85 - 94
		step	gobo6		104 - 113
		step	gobo7		114 - 132
		step	gobo8		133 - 151
		step	gobo9		152 - 170
		step	gobo10		171 - 191
		step	rot 1		192 - 203
		step	rot 2		204 - 215
		step	rot 3		216 - 227
		step	rot 4		228 - 239
		step	rot 5		240 - 255
4	COLOR	step	color 1		0 - 18
		step	color 2		19 - 27
		step	color 2,3		28 - 37
		step	color 3		38 - 46
		step	color 3,4		47 - 56
		step	color 4		57 - 65
		step	color 4,5		66 - 75
		step	color 5		76 - 84
		step	color 5,6		85 - 94
		step	color 6		95 - 103
		step	color 6,7		104 - 113
		step	color 7		114 - 122
		step	color 7,8		123 - 132
		step	color 8		133 - 141
		step	color 8,9		142 - 151
		step	color 9		152 - 160
		step	color 9,10		161 - 170
		step	color 10		171 - 191
		step	rot 1		192 - 203
		step	rot 2		204 - 215
		step	rot 3		216 - 227
		step	rot 4		228 - 239
		step	rot 5		240 - 255
5	RESET		OFF		0 - 127
			ON		128 - 255
6	SHUTTER	step	closed		0 - 64
		step	open		65 - 128
		step	strobe speed 1	1Hz	129 - 142
		step	strobe speed 2	2Hz	143 - 156
		step	strobe speed 3	3Hz	157 - 170
		step	strobe speed 4	4Hz	171 - 184
		step	strobe speed 5	5Hz	185 - 198
		step	strobe speed 6	6Hz	199 - 212
		step	strobe speed 7	7Hz	213 - 240
		step	open		241 - 255
7	DIMMER	proportional		0 / 100%	0 - 255
8	NOT USED				
9	NOT USED				
10	LAMP ON-OFF		OFF		0 - 127
			ON		128 - 255
NOTE 1 : dip-switch 10 and 9 must be ON = MASTER MODE					
NOTE 2 : dip-switch 10 = SLAVE MODE					
NOTE 3 : dip-switch 10, 9, 8 must be ON = MASTER MODE with STROBE EFFEKT					
NOTE 4 : dip-switch 10, 9, 8, 7 must be ON = TEST MODE					
NOTE 4 : dip-switch 10, 9, 8, 7, 6 must be ON = SET-UP DURING THE MANUFACTURE					
NOTE 5 : dip-switch 10, 9, 8, 7, 6, 5 must be ON = BICOLOR SET-UP DURING THE MANUFACTURE					